

# SVCS multi zone control panel



Input for fire alarm, break glass call points, smoke detectors and heat detectors.

72 hour battery back up on mains failure.  
Sealed lead acid batteries.  
Auto cut off to protect batteries.  
Relay to provide volt free fault indication.  
Open circuit cable detect (issues a coded fault signal).

Auto-Reset Test – Front of panel keyswitch enables the smoke heads to be reset after smoke detection and/or test the opening & closing of all actuators/vents connected.

Facility for smoke heads to automatically reset.

Each zone has Input for:

Breakglass callpoints  
Smoke detectors  
Fire alarm volt free contacts (N/O)  
Override switch

Alternatively a zone can be set as a slave to open or close when any master zone is triggered

## **VOLTAGE SUPPLY**

**230 Vac**

## **VOLTAGE OUTPUT**

**24v up to 200amp (10 amp max load/zone card)**

## **ELECTRIC CONNECTION**

**2 wire polarity inversion or 3 wires drive open drive close**

## **DRIVE TIME**

**Adjustable 1-100 seconds**

