

# VCS-1 control panel



**Single zone 10 amp control panel with extra inputs and functions.**

72 hour battery back up on mains failure.  
300mm x 200mm x 150mm IP65 steel enclosure.  
Sealed lead acid batteries.  
Auto cut off to protect batteries.  
Relay to provide volt free fault indication.  
Close/Auto/Open Function  
Front of panel keyswitch to control open/close  
function of actuators/vents (full override priority).  
Facility to connect smoke heads to automatically  
reset once smoke has cleared.  
Variable opening of vents  
(Option; specify when ordering)

Inputs for:  
Breakglass callpoints  
Smoke detectors  
Fire alarm volt free aux. contacts  
Firemans Override switch  
Optically Isolated inputs  
(BMS or variable manual controls)  
Thermostat (option)  
Rain sensor (option)  
Wind sensor (option)  
Outputs for:  
2/3wired 24v actuators up to 10amp load

<b>VOLTAGE SUPPLY</b>	<b>230 Vac</b>
<b>VOLTAGE OUTPUT</b>	<b>24v 10 amp max load</b>
<b>ELECTRIC CONNECTION</b>	<b>2 wire polarity reversal or 3 wires drive open drive close</b>
<b>DRIVE TIME</b>	<b>Adjustable 1-100seconds</b>



Smoke Control Systems Limited Unit1 Cymbio Business Centre, Northway Lane, Tewkesbury, Glos. GL20 8JG  
Tel:0844 499 6366 Fax:0844 499 6367 Email:info@smokecontrolsystems.co.uk www.smokecontrolsystems.co.uk